

First Time Optimisation Of Varilight V-Pro Dimmers with LEDLite SMD Lamps.

JQP dimmers are supplied pre set in Mode 1

Selecting Mode 2.

1. Set the dimmer knob to the maximum position with the lamps switched on.
2. Turn the dimmer off & on 3 times (each time it is switched on wait for the lamps to illuminate).
3. The lights will step up & down to show that the dimmer is in configuration mode.
4. Select mode 2 by turning the dimmer knob to the minimum & leave it there for 5 seconds.
5. The lights will flash twice to show that it is now in mode 2.
6. The minimum brightness can now be adjusted if required using the instructions provided with the dimmer.